



XONOX ARGENTINA SRL

Cabildo 619, (1870) Avellaneda, Buenos Aires, Argentina

☎ 54 (11) 4208-8091 📠 54 (11) 4209-0222

✉: xonox@ciudad.com.ar 🌐 <http://www.xonox.com.ar>

CARACTERÍSTICAS DE DRIVERS



2445



D-7652E



D-7250



D-250



PY-220



ZT-4401



2425



RF-850

MODELO	IMAN (ONZAS)	Ø BOBINA (MM)	DIAFRAGMA	ROSCA (PULGADAS)	IMPEDANCIA (OHMS)	POTENCIA (WATTS) (RMS / MAXIMA)	RESPUESTA (HZ)
RF-850	65	74,1	TITANIO	2	8	150 / 300	500-20K
D-250	50	74,1	TITANIO	2	8	100 / 200	500-20K
PY-220	40	50,8	TITANIO	1	8	75 / 50	500-20K
ZT-4401	20	44,4	TITANIO	1	8	50 / 100	1K-20K
2445	100	99,2	TITANIO	2	8 o 16	100 / 200	500-20K
D-7652E	50	76,2	TITANIO	2	8 o 16	75 / 150	500-18K
D-7250	50	72,2	TITANIO	2	8 o 16	75 / 150	500-18K
2425	40	44,45	TITANIO	1	8 o 16	50 / 100	800-20K